

Claims:

1. An electrochemical system comprising

a plurality of cells;
- 5 a measuring device including a plurality of inputs connected across the plurality of cells to generate voltage and current signals indicative of voltage and current characteristics of the plurality of cells;

a current supply/draw means for superimposing modulated current values through the plurality of cells; and,
- 10 a controller for controlling at least one system operating condition based on the voltage and current characteristics received from the measuring device, the controller being connected to the measuring device.
2. The electrochemical system as defined in claim 1 wherein the current supply/draw means comprises a modulator.
- 15 3. The electrochemical system as defined in claim 2 wherein the modulator is an integral part of the controller.
4. The electrochemical system as defined in claim 2 wherein the plurality of inputs are connected across individual cells in the plurality of cells and the modulator is operable to superimpose modulated current values
20 through the individual cells.
5. The electrochemical system as defined in claim 2 wherein the controller is operable to control, in real time, the at least one system operating condition based on the voltage and current characteristics received from the measuring device.
- 25 6. The electrochemical system as defined in claim 2, wherein the controller is operable to alert an operator based on alarm conditions

determined from the voltage and current characteristics received from the measuring device.

7. The electrochemical system as claimed in claim 2, wherein the modulator is arranged to superimpose the modulated current values in burst
5 time periods for high frequency resistance measurement, with time periods between burst time periods of no superimposition of modulated current values.
8. The electrochemical system as claimed in claim 2, wherein the measuring device provides a plurality of primary channels for the measured
10 voltage and current signals, there being one channel for the voltage across each cell, and wherein the measuring device includes a splitter for separating out at least the DC components of the voltages across the individual cells from the primary channels, the splitter having first channels as outputs for the DC components.
- 15 9. The electrochemical system as claimed in claim 8, wherein the splitter includes second channels as outputs for the AC components of the voltages across the individual cells.
10. The electrochemical system as claimed in claim 8, wherein the measuring device includes a plurality of instrumentation amplifiers connected
20 to the inputs of the measuring device and having outputs providing the plurality of the primary channels and an analog multiplexer connected to at least the first channels from the channel splitter, wherein a multiplexer control line is connected between the controller and the analog multiplexer for controlling the analog multiplexer to switch sequentially between at least the
25 first channels.
11. The electrochemical system as claimed in claim 10, which further includes a first analog to digital converter connected to the output of the analog multiplexer, a voltage data bus connected between the first analog to digital converter and the controller and an analog to digital control line

connected between the controller and the first analog to digital converter for control thereof.

12. The electrochemical system as claimed in claim 11, wherein a current sensing device is provided connected in series with the individual cells
5 for measuring the current, wherein the current sensing device is connected to the controller.

13. The electrochemical system as claimed in claim 12, wherein outputs of the current sensing device are connected to a current amplifier and wherein the current amplifier has an output for a current measurement signal
10 connected to the controller.

14. The electrochemical system as claimed in claim 12, wherein a current analog to digital converter is provided having an input connected to the output of the current amplifier and having a current output and a control input and wherein a data bus connects the current output to the controller and
15 an analog to digital control line is provided between the controller and the control input of the current analog to digital converter.

15. The electrochemical system as claimed in claim 2, wherein the controller includes an input, connectable to a computing device for supply of control signals for controlling the controller.

20 16. The electrochemical system as claimed in claim 1, further comprising a load powered by the plurality of cells.

17. A method of controlling at least one system operating condition of a multi-cell electrochemical system, the method comprising:

(a) superimposing modulated current values across a plurality of
25 cells of the electrochemical device;

(b) drawing current from the plurality of cells to generate voltage and current signals indicative of voltage and current characteristics of the plurality of cells; and,

(c) controlling the at least one system operating condition based
5 on the voltage and current characteristics of the plurality of cells.

18. The method as defined in claim 17 wherein

step (a) comprises superimposing the modulated current values across individual cells in the plurality of cells; and

step (b) comprises drawing current from the individual cells to
10 generate voltage and current signals indicative of voltage and current characteristics of the individual cells.

19. The method as claimed in claim 17, wherein step (a) is performed in burst time periods for high frequency resistance measurement, with time periods between burst time periods of no superimposition of
15 modulated current values.

20. The method as claimed in claim 19, wherein step (a) comprises controlling the superimposing to provide a series of set interference conditions, and measuring, for each interference condition, at least some of the voltage and current characteristics of the electrochemical device.

20 21. A method as claimed in claim 20 wherein

step (a) comprises varying a frequency of the superimposed current values;

step (b) comprises generating the voltage and current signals at selected frequencies for the superimposed modulated current values, and
25 determining from the voltage and current signals a plurality of real and imaginary components of the impedance of the individual cells; and,

step (c) comprises controlling the at least one system operating condition based on the plurality of real and imaginary components of the impedance of the individual cells.

22. A method as claimed in claim 19, wherein step (b) comprises
5 connecting inputs of a plurality of differential amplifiers across individual cells of the electrochemical device, measuring the voltage and current of the cells with the plurality of differential amplifiers to generate the voltage and current signals, supplying the voltage and current signals to a multiplexer and operating the multiplexer to sequentially supply the voltage and current
10 signals to a controller for performing step (c).

23. A method as claimed in claim 22, further comprising converting each voltage and current signal selected by the analog multiplexer to a digital signal in a voltage analog to digital converter.

24. A method as claimed in claim 23, further comprising providing a
15 current sensing device connected in series with the cells for measuring the current through the load, measuring the voltage across the current sensing device to determine the current through the load and thereby generating a current measurement signal, and supplying the current measurement signal to the controller.

20 25. A method as claimed in claim 24, further comprising converting the current measurement signal to a digital current measurement signal, and supplying the digital current measurement signal to the controller.

26. A method as claimed in claim 17, further comprising driving a load using current drawn from the plurality of cells.